

## uFace 602



### ➔ Multi-Biometric T&A and Access Control System

Face capacity : 1200 (1:N), 3000 (1:1)  
 Fingerprints templates : 2000 (Optional 4000)  
 Card Storage : 10,000  
 Transaction storage : 1,00,000  
 Card reader : Yes  
 CPU : 1.0GHz  
 Fingerprint sensor : 500 DPI Optical sensor  
 FAR :  $\leq 0.0001\%$  | FRR :  $\leq 1\%$   
 Identification speed :  $< 0.5$  sec  
 Algorithm Ver : 10  
 Display : 4.3-Inch Touch Screen  
 LED Indicator : Green/Red  
 Schedule Bell/Speaker : Mini Speaker  
 Communication : TCP/IP, RS232/485, USB Host  
 (Optional : Wifi, GPRS)  
 Push data : Yes  
 Power Supply : 12V 3A  
 Operating Temperature : 0 °C - 45 °C  
 Operating Humidity : 20% - 80%  
 Dimension : 194.1x169x109.0mm  
 Wiegand : Output

Relay : 12 V relay for lock EM lock, Bolt Lock or Strike lock

Support Fire Alarm : Yes

Door Sensor : Yes | Anti Passback : Yes

Door Bell : Yes | Support exit readers : Yes

#### Optional :

Battery : 7.4 V, 2000 mAh Backup Battery

Card readers : No | Communication : No | Sensor : No

Printer : Optional

#### Compatibility:

- Compatible with Multi Door controllers via weigand

- External Speaker output available (Optional)

- External Bulb output available (Optional)

- Support External Printer

#### Compatible Software and SDK:

- Smart office suite desktop and web

- etime track lite desktop & web

- SDK for desktop applications

- Web based Device Manager/ePush server using Push data.

Helps developers & integrators

- Supports 3rd Party Payroll/HRMS/ERP and

Other applications